

855

Purchase Order Acknowledgment

Functional Group=PR

This Draft Standard for Trial Use contains the format and establishes the data contents of the Purchase Order Acknowledgment Transaction Set (855) for use within the context of an Electronic Data Interchange (EDI) environment. The transaction set can be used to provide for customary and established business and industry practice relative to a seller's acknowledgment of a buyer's purchase order. This transaction set can also be used as notification of a vendor generated order. This usage advises a buyer that a vendor has or will ship merchandise as prearranged in their partnership.

Heading:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
010	ST	Transaction Set Header	M	1			Must use
020	BAK	Beginning Segment for Purchase Order Acknowledgment	M	1			Must use
<u>LOOP ID - N1</u>					<u>200</u>		
300	N1	Name	O	1			Used
310	N2	Additional Name Information	O	2			Used
320	N3	Address Information	O	2			Used
330	N4	Geographic Location	O	1			Used

Detail:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<u>LOOP ID - PO1</u>					<u>100000</u>	<u>N2/010L</u>	
010	PO1	Baseline Item Data	O	1		N2/010	Used
<u>LOOP ID - PID</u>					<u>1000</u>		
050	PID	Product/Item Description	O	1			Used
<u>LOOP ID - ACK</u>					<u>104</u>		
270	ACK	Line Item Acknowledgment	O	1			Used

Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Notes</u>	<u>Usage</u>
<u>LOOP ID - CTT</u>					<u>1</u>	<u>N3/010L</u>	
010	CTT	Transaction Totals	O	1		N3/010	Used
030	SE	Transaction Set Trailer	M	1			Must use

Notes:

- 2/010L PO102 is required.
- 2/010 PO102 is required.
- 3/010L The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.
- 3/010 The number of line items (CTT01) is the accumulation of the number of PO1 segments. If used, hash total (CTT02) is the sum of the value of quantities ordered (PO102) for each PO1 segment.

ST Transaction Set Header

Pos: 010	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the start of a transaction set and to assign a control number

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ST01	143	Transaction Set Identifier Code	M	ID	3/3	Must use
		Description: Code uniquely identifying a Transaction Set				
		<u>Code</u>		<u>Name</u>		
		855		Purchase Order Acknowledgment		
ST02	329	Transaction Set Control Number	M	AN	4/9	Must use
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

Semantics:

1. The transaction set identifier (ST01) used by the translation routines of the interchange partners to select the appropriate transaction set definition (e.g., 810 selects the Invoice Transaction Set).

BAK Beginning Segment for Purchase Order Acknowledgment

Pos: 020	Max: 1
Heading - Mandatory	
Loop: N/A	Elements: 6

User Option (Usage): Must use

To indicate the beginning of the Purchase Order Acknowledgment Transaction Set and transmit identifying numbers and dates

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
BAK01	353	Transaction Set Purpose Code	M	ID	2/2	Must use
		Description: Code identifying purpose of transaction set				
		<u>Code</u>		<u>Name</u>		
		06		Confirmation		
BAK02	587	Acknowledgment Type	M	ID	2/2	Must use
		Description: Code specifying the type of acknowledgment				
		<u>Code</u>		<u>Name</u>		
		AD		Acknowledge - With Detail, No Change		
BAK03	324	Purchase Order Number	M	AN	1/22	Must use
		Description: Identifying number for Purchase Order assigned by the orderer/purchaser				
BAK04	373	Date	M	DT	8/8	Must use
		Description: Date expressed as CCYYMMDD				
BAK05	328	Release Number	O	AN	1/30	Used
		Description: Number identifying a release against a Purchase Order previously placed by the parties involved in the transaction				
BAK08	127	Reference Identification	O	AN	1/30	Used
		Description: Reference information as defined for a particular Transaction Set or as specified by the Reference Identification Qualifier				

Semantics:

1. BAK04 is the date assigned by the purchaser to purchase order.
2. BAK08 is the seller's order number.
3. BAK09 is the date assigned by the sender to the acknowledgment.

Loop N1

Pos: 300	Repeat: 200
Optional	
Loop: N1	Elements: N/A

User Option (Usage): Used

To identify a party by type of organization, name, and code

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
300	N1	Name	O	1		Used
310	N2	Additional Name Information	O	2		Used
320	N3	Address Information	O	2		Used
330	N4	Geographic Location	O	1		Used

N1**Name**

Pos: 300	Max: 1
Heading - Optional	
Loop: N1	Elements: 4

User Option (Usage): Used

To identify a party by type of organization, name, and code

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N101	98	Entity Identifier Code	M	ID	2/3	Must use
		Description: Code identifying an organizational entity, a physical location, property or an individual				
		<u>Code</u>		<u>Name</u>		
		BT		Bill-to-Party		
		BY		Buying Party (Purchaser)		
		ST		Ship To		
N102	93	Name	X	AN	1/60	Used
		Description: Free-form name				
N103	66	Identification Code Qualifier	X	ID	1/2	Used
		Description: Code designating the system/method of code structure used for Identification Code (67)				
		<u>Code</u>		<u>Name</u>		
		91		Assigned by Seller or Seller's Agent		
N104	67	Identification Code	X	AN	2/80	Used
		Description: Code identifying a party or other code				

Syntax Rules:

1. R0203 - At least one of N102 or N103 is required.
2. P0304 - If either N103 or N104 is present, then the other is required.

Comments:

1. This segment, used alone, provides the most efficient method of providing organizational identification. To obtain this efficiency the "ID Code" (N104) must provide a key to the table maintained by the transaction processing party.
2. N105 and N106 further define the type of entity in N101.

N2 Additional Name Information

Pos: 310	Max: 2
Heading - Optional	
Loop: N1	Elements: 1

User Option (Usage): Used

To specify additional names or those longer than 35 characters in length

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N201	93	Name	M	AN	1/60	Must use

Description: Free-form name

N3 Address Information

Pos: 320	Max: 2
Heading - Optional	
Loop: N1	Elements: 1

User Option (Usage): Used

To specify the location of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N301	166	Address Information	M	AN	1/55	Must use
		Description: Address information				

N4 Geographic Location

Pos: 330	Max: 1
Heading - Optional	
Loop: N1	Elements: 3

User Option (Usage): Used

To specify the geographic place of the named party

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
N401	19	City Name	O	AN	2/30	Used
Description: Free-form text for city name						
N402	156	State or Province Code	O	ID	2/2	Used
Description: Code (Standard State/Province) as defined by appropriate government agency						
N403	116	Postal Code	O	ID	3/15	Used
Description: Code defining international postal zone code excluding punctuation and blanks (zip code for United States)						

Syntax Rules:

1. C0605 - If N406 is present, then N405 is required.

Comments:

1. A combination of either N401 through N404, or N405 and N406 may be adequate to specify a location.
2. N402 is required only if city name (N401) is in the U.S. or Canada.

Loop PO1

Pos: 010	Repeat: 100000
Optional	
Loop: PO1 Elements: N/A	

User Option (Usage): Used

To specify basic and most frequently used line item data

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
010	PO1	Baseline Item Data	O	1		Used
050		Loop PID	O		1000	Used
270		Loop ACK	O		104	Used

PO1 Baseline Item Data

Pos: 010	Max: 1
Detail - Optional	
Loop: PO1	Elements: 8

User Option (Usage): Used

To specify basic and most frequently used line item data

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PO101	350	Assigned Identification	O	AN	1/20	Used
		Description: Alphanumeric characters assigned for differentiation within a transaction set				
PO102	330	Quantity Ordered	X	R	1/15	Used
		Description: Quantity ordered				
PO103	355	Unit or Basis for Measurement Code	O	ID	2/2	Used
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		<u>Code</u>		<u>Name</u>		
		CA		Case		
		EA		Each		
PO104	212	Unit Price	X	R	1/17	Used
		Description: Price per unit of product, service, commodity, etc.				
PO106	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		<u>Code</u>		<u>Name</u>		
		VA		Vendor's Style Number		
		VC		Vendor's (Seller's) Catalog Number		
		VI		Vary Item Product Number		
		VN		Vendor's (Seller's) Item Number		
		VP		Vendor's (Seller's) Part Number		
PO107	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				
PO108	235	Product/Service ID Qualifier	X	ID	2/2	Used
		Description: Code identifying the type/source of the descriptive number used in Product/Service ID (234)				
		<u>Code</u>		<u>Name</u>		
		CB		Buyer's Catalog Number		
		IN		Buyer's Item Number		
		N4		National Drug Code in 5-4-2 Format		
		ND		National Drug Code (NDC)		
		PI		Purchaser's Item Code		
		UP		U.P.C. Consumer Package Code (1-5-5-1)		
PO109	234	Product/Service ID	X	AN	1/48	Used
		Description: Identifying number for a product or service				

Syntax Rules:

1. C0302 - If PO103 is present, then PO102 is required.
2. C0504 - If PO105 is present, then PO104 is required.
3. P0607 - If either PO106 or PO107 is present, then the other is required.
4. P0809 - If either PO108 or PO109 is present, then the other is required.
5. P1011 - If either PO110 or PO111 is present, then the other is required.
6. P1213 - If either PO112 or PO113 is present, then the other is required.
7. P1415 - If either PO114 or PO115 is present, then the other is required.
8. P1617 - If either PO116 or PO117 is present, then the other is required.
9. P1819 - If either PO118 or PO119 is present, then the other is required.
10. P2021 - If either PO120 or PO121 is present, then the other is required.
11. P2223 - If either PO122 or PO123 is present, then the other is required.
12. P2425 - If either PO124 or PO125 is present, then the other is required.

Comments:

1. See the Data Element Dictionary for a complete list of IDs.
2. PO101 is the line item identification.
3. PO106 through PO125 provide for ten different product/service IDs per each item. For example: Case, Color, Drawing No., U.P.C. No., ISBN No., Model No., or SKU.

Loop PID

Pos: 050	Repeat: 1000
Optional	
Loop: PID	Elements: N/A

User Option (Usage): Used

To describe a product or process in coded or free-form format

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
050	PID	Product/Item Description	O	1		Used

PID Product/Item Description

Pos: 050	Max: 1
Detail - Optional	
Loop: PID	Elements: 2

User Option (Usage): Used

To describe a product or process in coded or free-form format

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
PID01	349	Item Description Type	M	ID	1/1	Must use
		Description: Code indicating the format of a description				
		<u>Code</u>		<u>Name</u>		
		F		Free-form		
PID05	352	Description	X	AN	1/80	Used
		Description: A free-form description to clarify the related data elements and their content				

Syntax Rules:

1. C0403 - If PID04 is present, then PID03 is required.
2. R0405 - At least one of PID04 or PID05 is required.
3. C0703 - If PID07 is present, then PID03 is required.
4. C0804 - If PID08 is present, then PID04 is required.
5. C0905 - If PID09 is present, then PID05 is required.

Semantics:

1. Use PID03 to indicate the organization that publishes the code list being referred to.
2. PID04 should be used for industry-specific product description codes.
3. PID08 describes the physical characteristics of the product identified in PID04. A "Y" indicates that the specified attribute applies to this item; an "N" indicates it does not apply. Any other value is indeterminate.
4. PID09 is used to identify the language being used in PID05.

Comments:

1. If PID01 equals "F", then PID05 is used. If PID01 equals "S", then PID04 is used. If PID01 equals "X", then both PID04 and PID05 are used.
2. Use PID06 when necessary to refer to the product surface or layer being described in the segment.
3. PID07 specifies the individual code list of the agency specified in PID03.

Loop ACK

Pos: 270	Repeat: 104
Optional	
Loop: ACK Elements: N/A	

User Option (Usage): Used

To acknowledge the ordered quantities and specify the ready date for a specific line item

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
270	ACK	Line Item Acknowledgment	O	1		Used

ACK Line Item Acknowledgment

Pos: 270	Max: 1
Detail - Optional	
Loop: ACK	Elements: 3

User Option (Usage): Used

To acknowledge the ordered quantities and specify the ready date for a specific line item

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
ACK01	668	Line Item Status Code	M	ID	2/2	Must use
		Description: Code specifying the action taken by the seller on a line item requested by the buyer				
		<u>Code</u>		<u>Name</u>		
		BP		Item Accepted - Partial Shipment, Balance Backordered		
		IA		Item Accepted		
		IB		Item Backordered		
ACK02	380	Quantity	X	R	1/15	Used
		Description: Numeric value of quantity				
ACK03	355	Unit or Basis for Measurement Code	X	ID	2/2	Used
		Description: Code specifying the units in which a value is being expressed, or manner in which a measurement has been taken				
		<u>Code</u>		<u>Name</u>		
		PC		Piece		

Syntax Rules:

1. P0203 - If either ACK02 or ACK03 is present, then the other is required.
2. C0405 - If ACK04 is present, then ACK05 is required.
3. P0708 - If either ACK07 or ACK08 is present, then the other is required.
4. P0910 - If either ACK09 or ACK10 is present, then the other is required.
5. P1112 - If either ACK11 or ACK12 is present, then the other is required.
6. P1314 - If either ACK13 or ACK14 is present, then the other is required.
7. P1516 - If either ACK15 or ACK16 is present, then the other is required.
8. P1718 - If either ACK17 or ACK18 is present, then the other is required.
9. P1920 - If either ACK19 or ACK20 is present, then the other is required.
10. P2122 - If either ACK21 or ACK22 is present, then the other is required.
11. P2324 - If either ACK23 or ACK24 is present, then the other is required.
12. P2526 - If either ACK25 or ACK26 is present, then the other is required.
13. P2728 - If either ACK27 or ACK28 is present, then the other is required.
14. C282729 - If ACK28 is present, then ACK27 and ACK29 are required.

Semantics:

1. ACK29 Industry Reason Code may be used to identify the item status. In addition, it may be used in conjunction with ACK01 to further clarify the status.

Loop CTT

Pos: 010	Repeat: 1
Optional	
Loop: CTT	Elements: N/A

User Option (Usage): Used

To transmit a hash total for a specific element in the transaction set

Loop Summary:

<u>Pos</u>	<u>Id</u>	<u>Segment Name</u>	<u>Req</u>	<u>Max Use</u>	<u>Repeat</u>	<u>Usage</u>
010	CTT	Transaction Totals	O	1		Used

CTT Transaction Totals

Pos: 010	Max: 1
Summary - Optional	
Loop: CTT	Elements: 1

User Option (Usage): Used

To transmit a hash total for a specific element in the transaction set

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
CTT01	354	Number of Line Items	M	NO	1/6	Must use

Description: Total number of line items in the transaction set

Syntax Rules:

1. P0304 - If either CTT03 or CTT04 is present, then the other is required.
2. P0506 - If either CTT05 or CTT06 is present, then the other is required.

Comments:

1. This segment is intended to provide hash totals to validate transaction completeness and correctness.

SE Transaction Set Trailer

Pos: 030	Max: 1
Summary - Mandatory	
Loop: N/A	Elements: 2

User Option (Usage): Must use

To indicate the end of the transaction set and provide the count of the transmitted segments (including the beginning (ST) and ending (SE) segments)

Element Summary:

<u>Ref</u>	<u>Id</u>	<u>Element Name</u>	<u>Req</u>	<u>Type</u>	<u>Min/Max</u>	<u>Usage</u>
SE01	96	Number of Included Segments	M	NO	1/10	Must use
		Description: Total number of segments included in a transaction set including ST and SE segments				
SE02	329	Transaction Set Control Number	M	AN	4/9	Must use
		Description: Identifying control number that must be unique within the transaction set functional group assigned by the originator for a transaction set				

Comments:

1. SE is the last segment of each transaction set.